

BC-200

Automatic No-Bark, Rechargeable

1. Set Up Collar: Charge 14-16 hours
2. Auto – Set Technology, the No Bark Collar automatically sets itself at the appropriate stimulation that quiets your dog. It also gives your dog a two – second “learning time-out” between stimulations.

Troubleshooting Tips

1. Probe selection: Both probes need to be same length (short or long)
2. Charging: Uses 12-volt, 200 mAmp DC adapter
Full charge takes 14-16 hours and lasts 1-2 months dep. on use.
3. Check operation: Rub the probes on a hard, non-glass surface and see if the light come on. Receiver is working if a red light comes on briefly when rubbed
4. Collar fit: 1 finger allowed to slide under strap at back of dog's neck
Probes positioned 1" above or below dog's Adam's apple
Both probes must make skin contact
5. Not taking a charge: Check adapter and outlet
6. No lights on collar: Customer must completely charge the collar before putting it on dog for the first time
7. Reset Stimulation: Put collar on charger for 10-15 minutes, correction level will go to level 1

BC-200 Features

| | | |
|----------|--|---|
| Adapter: | 12-volt, 200 mA, DC | |
| Collar: | Waterproof, rechargeable, and microline Measures 1.95" wide x 1.36" tall x 1.17" thick and weighs 3.2 oz. Circumference = 2.5 – 7.5 inches | |
| Lights: | Blinking red once every 5 seconds Pulsating red Solid Red | Low battery indicator Reset period after delivering stimulation Delivering Stimulation |

Resets After Charging: Will Reset after charging to level 1.

Video-56